General Hinge Information

Special Situation Products

- "CE" Concealed electric hinges conduct current regardless of door position to electric locks, exit devices, or hold open devices where tamper-proof hinge is required. Also to transmit signals from code readers on doors to remote computers for access control
- No electrical parts are exposed when hinge is installed
- Permanent fast pin
- Hinges should be installed in the center hinge location
- Not available as swing clear or raised barrel
- Hinges may be equipped with both concealed wires and concealed switches. When both are desired on the same hinge use prefix "CECS"
- Packed one per box with all machine screws and installlation instructions
- When ordering specify class number, size, finish and number of wires Suffix -54 for 4 wires, 56 for 6 wires -66 for 6 wires (2@24AWG, 4@28AWG), 58 for 8 wires or 10 for 10 wires
- Should be used along with a junction box
- Can be furnished with hospital tips





Electrical Ratings						
Suffix	# Wires	Wire Gage	Volts (AC or DC)			
			6, 12, 24	48		
		Current				
-54	4	28AWG	1 amp/wire	5 milli-amp/wire		
-56	6	28AWG	.7 amp/wire	5 milli-amp/wire		
-58	8	28AWG	.5 amp/wire	5 milli-amp/wire		
-10	10	28AWG	.4 amp/wire	5 milli-amp/wire		
-66*	6	2@24AWG	2 amp/wire	5 milli-amp/wire		
		4@28AWG	1 amp/wire	5 milli-amp/wire		
18**	8	2@18AWG	10amp/wire	5 milli-amp/wire		
		6@28AWG	.7amp/wire	5 milli-amp/wire		

Inrush 15A for .05 second/wire


- "CE" hinges are listed by UL at these ratings
- * Not available in FBB168 and FBB199
- ** -18 and -12C are only available on models CB168, CB179, CB191 & CB-199.


JB2R - Junction Box

- Note: Install in middle hinge location
- Can be shop welded or field installed before frames are set
- Fits either 41/2" (114mm) or 5" (127mm) size hinges

Class Number				
CB179,	FBB179,	CB1900R	Sizes Available	
CB168,	FBB168,	CB1901R	4 1/2" x 4"	(114mm x 102mm)
CB191,	FBB191,	CB1960R	4 1/2" x 4 1/2"	(114mm x 114mm)
CB199,	FBB199,	CB1961R	5" x 4"	(127mm x 102mm)
			5" x 4 1/2"	(127mm x 114mm)
			5" x 5"	(127mm x 127mm)
			6" x 4 1/2"	(152mm x 114mm)
			6" x 5" *	(152mm x 127mm)
			6" x 6" *	(152mm x 152mm)

^{*} Not available in CB191, FBB191, CB1900R and CB1960R





Junction Box Top View

Right Side View